

Supermicro SuperChassis 826BE2C-R741JBOD 2U 12xLFF 12G SAS/SATA DUAL EXP 740W 1+1

Kod producenta: CSE-826BE2C-R741JBOD



Form Factor	Rack 2U
Host Interface	SAS 12Gbps
HDD Interface	SAS3, SATA
SAS Expander	Dual
Management	IPMI RJ45 port
Hot-swap 3.5" bays	12
Connectors	8 x SFF-8644
PSU	Redundant
Dimensions	437 x 89 x 647mm
PSU Wattage	740W
Rack Rails	included

Product SKUs



CSE-826BE2C-R741JBOD • SuperChassis
826BE2C-R741JBOD

Form Factor



• 2U JBOD storage chassis

Dimensions



Height - 3.5" (89 mm)
Width - 17.2" (437 mm)
Depth - 25.5" (647 mm)
Net Weight - 55 lbs (24.95 kg)
Gross Weight - 60 lbs (27.22 kg)
Packaging - 26.7" (678 mm) x 11.4" (290 mm)
(W x H x L) x 34.5" (876 mm)
Available Color - Black

Drive Bays



- 12 x 3.5" hot-swap drive bay

Backplane



- 12-port 2U SAS3 12Gbps dual-expander backplane, support up to 12x 3.5-inch SAS3/SATA3 HDD/SSD

Front Panel



Buttons - Power On/Off button
- System Reset Button
- Unit Identification (UID) button
LEDs - 1 Network Activity LEDs

Systems Cooling



Fans - 3 x 80x38mm hot-swap cooling fan(s)

System Monitoring



- IPMI

Operating Environment (System)



Operating Temperature Range - 5°C - 35°C (41°F - 95°F)
Non-Operating Temperature Range - -40°C - 70°C (-40°F - 158°F)
Operating Relative Humidity Range - 8% - 90% (non-condensing)
Non-Operating Relative Humidity Range - 5% - 95% (non-condensing)

Power Supply

1U 740W Redundant Platinum Power Supply W/PMbus
Power Efficiency - 94%
Total Output Power and Input - 740W with Input 100 - 240Vac
AC Input Frequency - 50-60Hz
Dimensions (L x W x H) - 346 x 76 x 40 mm
Output Type - Backplanes (gold finger)
+12V - Max: 61.7A / Min: 0.2A (100Vac - 240Vac)
+5Vsb - Max: 4A / Min: 0A
- PDB-PT826-8824
- O/P: 12V/135A
Power Distributor - +5V Max: 40A
- +3.3V Max: 24A
- -12V Max: 0.6A
Certification - **Platinum Certified**

Regulatory (Power Supply)



- BSMI
Power Supply Safety / EMC - CCC
- FCC class A
- TUV/CB

Strona firmowa produktu:

<https://www.superstorage.pl/supermicro-superchassis-826be2c-r741jbod-2u-12x1ff-12g-sassata-dual-exp-740w-11-p-2898.html>